



Managed Desktop Service BIOS Settings

Viglen with Intel Strawberry Mountain (DQ67SW)/Crow Point (DQ67OW)
[serial number code: SWB/OW]

Version 1.1

To enter the BIOS settings utility press the **F2** key when the mainboard splash/POST screen is displayed.

Read the information at the right hand side of the screen for information about which keys to use to navigate around and change settings.

Exit

Load BIOS Defaults

Configuration

SATA Drivers

Chipset SATA Mode <IDE>

Security

Set Supervisor Password [xxxxx]
User Level Access <No Access>

Boot

Boot to Optical Devices <Disable>
Boot to Removable Devices <Disable>
USB Boot <Disable>

Boot Device Priority
<Network>
<Hard Disk Drives>

Boot Display Options

POST Function Hotkeys Displayed <Disable>
Expansion Card Text <Hide All>

Exit

Exit Saving Changes

Additional Information:

- This model is only supported on version 6.0 and later of the Managed Desktop Service.
- This model requires version 2.5 or later of the re-image CD.
- To use a re-image CD you need to set the **Boot to Optical Devices** option to **<Enabled>** and check the **Boot Device Priority** has **[CD/DVD-ROM Drive]** at the top. Remember to **disable** the **Boot to Optical Devices** option and ensure the **Boot Device Priority** is set correctly after using the re-image CD.